

SERVICE NOTE

EFFECT: MONACO GP COCKPIT/ 50¢ per play

NUMBER: 001

Instructions for 50¢ per play modification for Monaco GP Cockpit:

Materials: 1 piggy-backed set of IC's: 7432/7474(bottom)

Procedure:

To convert your games to 50¢ per play, the enclosed piggy-backed IC's must be mounted to one of the Monaco logic boards. Proceed

- as follows:
- 1. Turn off game and remove game back piece.
- Locate logic board #96577-P. This board is one of two logic boards mounted under the TV monitor. #96577-P is the lower of the two boards.
 - 3. Locate IC33 on this board.
- 4. Mount the piggy-backed IC's on top of IC33. Be careful to match up pin 1 on all IC's.
 - 5. Carefully solder pins 7, 13, and 14 directly to pins 7, 13, and 14 on 1C33.
 - 6. Turn the logic board over and carefully cut the etch leading from pin 7 of IC32.
 - 7. On top of the logic board, solder the blue wire from the piggy-backed chips to PIN 5 of IC125.
 - 8. Solder the RED wire to PIN 7 of IC32.
- 9. This completes the modification. The game should now play for 50¢. If you have any questions about this mod, don't hesitate to call the Gremlin factory at (714)277-8700.

Gremlin Industries, Inc. 8401 Aero Drive, San Diego, California 92123 • Telephone: (714) 277-8700

506 PERPLAY MOD. FOR MONACO GP COCKPIT:

e s

PIGGY-BACK IC'S 7432 /7474 (BOTTOM) 7432 - CUT OFF PINS, 1, 2, 3, 4, 5, 6, 11, 12+

7474 - CUT OFF PINS 1,2,3,4,5,6,9, PERCING 7432 ON TOP OFF 7474 JOIN THE 2 PIN 2'S. + PINS 14'S. 4 7432-14 TO 7474-10

" 7432-9 TO 7474-8 TO 7474-12.

4 7432-10 To 7474-11. ATTACH RED WIRE (3" LONG) TO 7432-10 ATTACH BLUE WIRE (3" LONG) TO 7432-8